

UNIVERSAL
COMPATIBILITY



PRE-WIRED



COMPATIBLE WITH
ALL ZEN REMOTE
CONTROLS



12-24 V AC/DC



Entrematic ZENXR2

EN

Pre-wired universal 2-channel receiver

ZENXR2

The new pre-wired universal receiver

ZENXR2 is a powerful two-channel universal 433.92 MHz receiver conveniently pre-cabled to speed-up installation time.

It can be used on virtually all the motors found in the field, even not Ditec branded; **customers can therefore benefit from all the advantages of the ZEN remote control product range in terms of safety and security.**

This two-channel 12-24 V AC/DC receiver is pre-cabled and is placed into a sturdy plastic container that can be fixed to a wall or placed inside other devices. It is also supplied with a removable BIXMR2 memory module which can store up to 200 transmitters.

The receiver features 2 relay contacts (1A / 30V N.O.) and a wire antenna (173 mm long) ensuring a high sensitivity; alternatively, it can be connected to an external antenna [GOL148REA].

ZENXR2 works with the Ditec Entrematic Dip Switch, Fixed code, Rolling code, AES 128-bit Encrypted and PROTECTED mode protocols and can also be used with the ZENPAD/ZEN MANAGER transmitter management system.

Technical specifications

Receiver	Frequency	Power supply	Channels	Output type	Code memory capacity
ZENXR2	433,92 MHz	12-24 V = 60 mA Max 12-24 V~ 100 mA Max	2 (configurable)	2 relay contacts 1A / 30V = (N.O.)	200

Compatibility with all Entrematic ZEN remote controls and digital radio keypad

Remote controls: ZEN2, ZEN4, ZEN2W, ZEN4W, ZEN2Y, ZEN2R, ZEN2G, ZEN2B, ZEN2C, ZEN4C, ZEN2MT, ZEN4MT

Digital radio keypad: AXK4



ZEN2 - ZEN4 - ZEN2W - ZEN4W

ZEN2Y, ZEN2R, ZEN2G, ZEN2B

ZEN2C, ZEN4C, ZEN2MT, ZEN4MT

AXK4

ZENPAD & ZEN MANAGER

Dimensions	Connection diagram	Channel configuration



Entrematic Italy S.p.A.

Largo U. Boccioni, 1 · 21040 Origgio (VA) · Italy

Tel +39 02 963911 · Fax: +39 02 9650314

ditec@entrematic.com

www.ditecentrematic.com · www.entrematic.com

